

# Petrol Generator 3000 rpm - 7,8 kw

Gasoline generator powered by 4 stroke OHV engine with electric start, for Industrial applications, large fuel tank providing long hour running, full frame for better protection, AVR for smooth voltage output, large muffler to reduce noise harmful effects, oil alert system with automatic engine shut-off, control panel with 2 sockets and breaker. Key Start

DESCRIPTION	GENERATOR MODEL	GG10000LE	GENERADOR
<b>GENERATOR SET</b>	REFERENCE		
	RATED POWER (Kw)	7,8	
	MAX. POWER (Kw)	8,2	
	FREQUENCY (Hz)	50	
	VOLTAGE (V)	220 v.	
	CURRENT (A)	34,0	
	SOCKETS	1x32A + 1x16A	
	DISPLAY	LED5	
	FUEL TANK CAPACITY (L)	25	
	RUNNING TIME - 50% LOAD (hr.)	7,5	
	NOISE LEVEL BEHIND - 7m. (dBA)	72 (92 LWA)	
	DC OUTPUT (V) / INTENSITY (A)	12 / 8.3	
BATTERY (Ah)	14 Ah		
<b>ENGINE</b>	ENGINE MODEL	<b>IC460</b>	<b>PANEL DE CONTROL</b> 
	POWER OUTPUT (HP/3000rpm)	16	
	STARTING METHOD	Electric + Recoil	
	DISPLACEMENT (cc)	459 cc	
	OIL CAPACITY (L)	1,6	
<b>ALTERNATOR</b>	ALTERNATOR	<b>A8L</b>	
	RATED POWER (kW)	8	
	POWER FACTOR (Cosφ)	1	
	VOLTAGE REGULATION	AVR / Brushes	
<b>LOGISTICAL DATA</b>	N.G. (kg.)	88	
	G.W. (kg.)	92	
	PRODUCT DIMENSIONS (mm)	670x540x555	
	BOX DIMENSIONS (mm)	690x560x580	
	CAPACITY (units/container)		

## RECOMMENDED SPARE PARTS

REF.	SPARE PARTS NAME	QTY	
	AIR FILTER CORE	1	
	OIL FILTER ELEMENT	1	
	FUEL FILTER ELEMENT	1	
	AVR	1	

## OPTIONAL ACCESSORIES

REF.	SPARE PARTS NAME	QTY	
	PUSH WHEEL KIT	1	